iMQ

SQ7131/SQ7133/SQ7135 **Brief Datasheet V1.6**

Page: 1/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

Version: V1.6

SQ7131/SQ7133/SQ7135

Low Power Secure ASIC, ECC-256/384, ECDSA, ECDH, AES-128/AES-256, SHA 256, TRNG

- **Basic Information**
 - Operating Voltage : 2.0V ~ 5.5V
 - Operating Temperature : -40°C ~ 85°C
- Security Features
 - Asymmetric H/W Accelerator
 - NIST Standard P-256 /P-384 Elliptic **Curve Support**
 - ECDSA: FIPS186-4 Elliptic Curve **Digital Signature**
 - ECDH: FIPS SP800-56A Key Agreement
 - Symmetric H/W Accelerator
 - FIPS 180-4 SHA-256 & FIPS 198-1 HMAC Hash Algorithm
 - FIPS-197 AES-128/256: Encrypt/Decrypt, Galois Field Multiply for GCM
 - Networking Key Management Support
 - **KDF-PRF/AES/HKDF** Calculation for TLS 1.2 & 1.3
 - ECDHE : Ephemeral key generation and key agreement
 - True Random Number Generator(TRNG)
 - Active Tamper Detection
 - Simple/Differential Power Analysis Attack Countermeasure (SPA/DPA)
 - Independent Internal Clock to Prevent **Glitch Attack**
 - 128-bit Unique UID
 - Certification
 - NIST CAVP : DRBG, AES, SHA2, ECDSA and HMAC
 - NIST ESV Certified and CMVP FIPS 140-3 Complied
 - STQC Level 2 certified
 - SESIP & PSA Level 3 certification ready



Package



SOP8

8-Lead DFN (3mm x 3mm)

- Secure Storage
 - Chip-Dependent Encryption Technology
 - Secure Storage for Key, X.509 Compressed Certificate, Data
 - Large User Data Storage : 5.6KB
- Communication Interface
 - SQ7131 supports standard I2C (Max: 1MHz)
 - SQ7133 supports standard SPI (Max: 10MHz@MODE3)
 - SQ7135 supports SWI (Single Wire Interface) (230.4Kbps)
- Applications
 - Accessory Authentication
 - System Anti-Cloning
 - End-to-End Encryption
 - Secure TLS 1.2 and 1.3 Communication
 - AloT Device Security
 - Secure Boot /Secure OTA

Page : 2/23

iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

1.	PREFACE	
2.	PIN ASSIGNMENT/DESCRIPTION	
2	.1 SQ7131 PIN Assignment/ Description	
2	.2 SQ7133 PIN Assignment/Description	.6
2	.3 SQ7135 PIN Assignment/Description	.7
3.	ELECTRICAL CHARACTERISTICS	
3		
3	.2 OPERATION CONDITIONS	.9
	3.2.1 Operation Conditions	
	3.2.2 I/O Characteristics	
3	.3 DC CHARACTERISTICS	
3	.4 Power-on Reset Characteristics	
3	.5 BROR CHARACTERISTICS	
3	.6 AC CHARACTERISTICS	
	3.6.1 AC Parameters	
	3.6.2 I2C Characteristics	
	3.6.3 SPI Characteristics	
	3.6.4 SWI Characteristics	
	.7 EEPROM CHARACTERISTICS	
	PENDIX A. PACKAGE INFORMATION	
	PENDIX C. PRODUCT NUMBER INFORMATION	
KEV	ISION HISTORY	23

Page: 3/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

1. Preface

SQ713x supports many hardware cryptographic accelerators: embedded high-quality TRNG (True Random Number Generator), SHA-256, asymmetric encryption ECC-384/ECC-256, and symmetric encryption AES-128/AES-256. It also has secure storage for ECC and AES keys storage.

The device is suitable for building high-security applications, such as IoT symmetric/asymmetric authentication, attestation, TLS1.2/1.3 secure connections, secure boot, secure OTA, and F/W protection, etc.

Secure storage for ECC and AES keys:

Кеу Туре	SQ713x	Note
AES Key (AES-128/256)	12	Slot 8~19
ECC Private Key – 256	7	Slot 1~7
ECC Private Key – 384	2	Slot 20,21
ECC Public Key – 256	4	Slot 24,26~28
ECC Public Key – 384	4	Slot 30,32~34


Table 1-1 AES and ECC Key Slots

Page: 4/23


iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.


2. Pin Assignment/Description

2.1 SQ7131 Pin Assignment/ Description










Pin No.	Pin Name	I/О Туре	Description
1	NC	-	No Connect
2	NC	-	No Connect
3 4	NC	-	No Connect
	VSS	GND	Ground
5	SDA	I/O	I2C Serial Data
6	SCL	I	I2C Serial Clock Input
7	NC	-	No Connect
8	VDD	Power	VDD power Supply

Page : 5/23

iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.




Pin No.	Pin Name	I/О Туре	Description					
1	CS		SPI, Chip Select					
2	MISO	0	SPI, Master In Slave Out					
3	NC	-	No Connect					
4	VSS	GND	Ground					
5	5 MOSI 6 SCLK		SPI, Master Out, Slave In					
6			SPI, Clock Input					
7	NC	-	No Connect					
8	VDD	Power	VDD power Supply					


Page: 6/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.



Version: V1.6

2.3 SQ7135 Pin Assignment/Description








Figure 2-6 Pin Assignment OF SQ7135 8-Lead DFN

Pin No.	Pin Name	I/О Туре	Function Description
1	NC	-	No Connect
2	NC	-	No Connect
3	NC	-	No Connect
4	VSS	GND	Ground
5	SDA	I/O	SWI, single wire input/output pin
6	GPIO	I/O	General purpose input/output
7	NC	-	No Connect
8	VDD	Power	Positive Power Supply

Page: 7/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet

3. Electrical Characteristics

3.1 Absolute Maximum Rating

The absolute maximum ratings are rated values which must not be exceeded during operation, even for an instant. Any one of the ratings must not be exceeded. If any absolute maximum rating is exceeded, a device may break down or its performance may be degraded, causing it to catch fire or explode resulting in injury to the user. Thus, when designing products which include this device, ensure that no absolute maximum rating value will ever be exceeded.

(V							
Parameter	Symbol	Pins	Ratings	Unit			
Supply Voltage	V_{DD}	-	-0.3 to 6.0	V			
Input Voltage	V _{IN}	All I/O pins	-0.3 to VDD+0.3	V			
Output Current(Total)	I _{OL}	All I/O pins	100	mA			
Storage Temperature	T _{STG}	-	-50 to 125	°C			

Page: 8/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

iMQ Technology Inc.

No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet

3.2 Operation Conditions

The following defines the electrical characteristics of the device when it is operated at voltage and temperature maximum/minimum values. Unless otherwise stated, the standard conditions were determined at "operating temperature 25°C and operating voltage VDD = 3.3 V."

3.2.1 **Operation Conditions**

Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
Supply Voltage	V_{DD}		2.0	3.3	5.5	V
Operating Temperature	Та		-40	25	85	°C

3.2.2 I/O Characteristics

C

Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
Input Low Voltage	VIL	VDD=5V, temperature=25 °C	0		0.3 VDD	V
Input High Voltage	Vih	VDD=5V, temperature=25 °C	0.7 VDD		VDD	V
Output Low Voltage	V _{OL}	VDD=5V, temperature=25 °C IOL= 3 mA	0		0.1 VDD	V
Output High Voltage	V _{OH}	VDD=5V, temperature=25 °C IOH= -3 mA	0.9VDD		VDD	V

Page: 9/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

3.3 DC Characteristics

Parameter	Symbol	Min.	Тур.	Max.	Unit
Supply Current in Operation Mode (Note)	IDD_N1	-	3.7	-	mA
Supply Current in Deep Sleep Mode	IDD_DS	-	0.3	-	uA
Supply Current in Operation MODE	IDD N2		4.3		mA
(During non-ECC Command Execution)			т.5		
Supply Current in Operation MODE	IDD N3		7		mA
(During ECC Command Execution)	כא_ססו		,		

Note: The condition is waiting for Commands.

Page: 10/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

Name : SQ7131/SQ7133/SQ7135 Brief Datasheet No. : TDDS01-S7131-EN(B)

3.4 Power-on Reset Characteristics

	Ta=-40~85°C								
Symbol	Description	Min.	Тур.	Max.	Unit				
tPPW	Power-on reset minimum pulse width	1	-	-	ms				
tPWUP	Warming-up time after a reset is clear and device ready	-	4	-	ms				
tVDD	Power supply rise time	0.5	-	5	ms				




Figure 3-1 Operation Timing of Power-on Reset

Note : In power-down process, the VDD must be 0V, then re-power-on to ensure the IC operating normal.

Page: 11/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet

Version: V1.6

Ta=-40~85℃

3.5 BROR Characteristics

Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
BROR detected voltage	VBROR_Falling	VDD fall time > tVDD (for tVDD please refer to <u>CH3.4</u> <u>Power-on Reset Characteristics)</u>	1.85	1.90	1.95	V

Page: 12/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

Name : SQ7131/SQ7133/SQ7135 Brief Datasheet No. : TDDS01-S7131-EN(B)

3.6 AC Characteristics

3.6.1 **AC Parameters**

Parameter	Symbol	Min.	Тур.	Max.	Unit
Power-Up HW Ready Time	T _{PU_RDY}	-	9.5	-	ms
Power-Up Ready Time –	- T		10 5		
Ready for Command	T _{CMD_RDY}	- 18.5	-	ms	
Standby Time, Entering the	т		20		
deep sleep mode	Т _{stb}	-	20		us
Wake-Up Ready Time, deep	The		7.4		mr
sleep mode	Tw _{ds_rdy}	-	2.4		ms

Note: The "Typ." value is based on 25°C room temperature, and the Sleep command will change this value.

Page: 13/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

3.6.2 **I2C Characteristics**

Parameter	Symbol	Min.	Max.	Unit
Clock Frequency	f _{SCL}	-	1	MHz
Hold Time Repeated START Condition	t _{HD;STA}	0.45	-	us
Low Period of SCL Clock	t _{LOW}	0.65	-	us
High Period of SCL Clock	t _{HIGH}	0.35	-	us
Setup Time for a Repeated START Condition	tsu;sta	0.35	-	us
Data Hold Time	t _{HD;DAT}	-	0.5	us
Data Setup Time	t _{su;dat}	0.1	-	us
Rise Time of Both SDA and SCL	tr	20	300	ns
Fall Time of both SDA and SCL	t _f	20	300	ns
Setup Time of STOP Condition	t _{su;sto}	0.6	-	us
Bus Free Time Between a STOP and START Condition	t _{BUF}	1.3	-	us
Capacitive Load for Each Bus Line	Cb	-	400	pF




Figure 3-2 I2C Timing Sequence

Page: 14/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

Name : SQ7131/SQ7133/SQ7135 Brief Datasheet No. : TDDS01-S7131-EN(B)

3.6.3 **SPI Characteristics**




Figure 3-3 SPI Timing Sequence

Parameter	Symbol	Min.	Max.	Unit
SPI Frequency	fSPI	-		
(VDD=2.7V~5.5V, <=55°C)			10	MHz
(VDD=2.7V~5.5V, >55°C)			8	MHz
(VDD=2.0V~2.7V)			5	MHz
SPI Period	tSPI	1/fSPI	-	ns
High period of the SCLK pin	tCLKH	0.4 tSPI	-	ns
Low period of the SCLK pin	tCLKL	0.4 tSPI	-	ns
From SPICS active to first sample edge	tCS_SU	2.0 tSPI	-	ns
From last SCLK shift edge to SPICS inactive	tCS_HD	2.0 tSPI	-	ns
Time between SPI transaction	tCS_WA	3.0 tSPI	-	ns
Data Input Setup Time ¹	tSI_SU	25	-	ns
Data Input Hold time ¹	tSI_HD	10	-	ns
Data Output Valid Time ¹	tSO_VD	-	40	ns
Data Output Disable Time ¹	tso_dis	-	25	ns

Note 1: These parameters are characterized but not tested in production.

Page: 15/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.

iMQ Technology Inc. No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet Version: V1.6 3.6.4 **SWI** Characteristics tBIT 43.4 us tLOW tSTART `tHIGH´ 4.34 us 4.34 us 4.34 us 0 Zero Token Start "0xFD"1111 1101b Stop tSTART

"0xFF"1111 1111b

One Token

Start

Figure 3-4 SWI Timing Sequence@230.4K (Typ.)

Stop





Figure 3-5 SWI Wake Token Timing Diagram



Page: 16/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet Version: V1.6

Parameter	Symbol	Direction ¹	Min.	Тур.	Max.	Unit
Start Token	tSTART	Input	4.10	4.34	4.56	μs
		Output	3.91	4.34	4.77	μs
Data Token High	tHIGH	Input	4.10	4.34	4.56	μs
		Output	3.91	4.34	4.77	μs
Data Token Low	tLOW	Input	4.10	4.34	4.56	μs
		Output	3.91	4.34	4.77	μs
Bit Time ²	tBIT	Input	41	43.4	46	μs
		Output	39	43.4	48	μs
Turn Around ³	tTURNAROUND	Input	10	-	-	μs
		Output	86	96	106	μs
Bus Timeout ⁴	tTIMEOUT	Input	65	-	-	ms

Note 1: Direction is with respect to SQ713x device. Input is from Master to SQ713x, Output is from SQ713x to Master.

Note 2: Bit Timing: tSTART, tLOW, tHIGH, and tBIT are designed to be compatible with a standard UART baud rate at 230.4 kbps. The UART is set to one start bit, eight data bits, no parity and one Stop bit.

Note 3 : Turnaround time: SQ713x will initiate the first output low going transition after this time interval following the initial falling edge of the start pulse of the last bit of the transmit flag. After SQ713x transmits the last bit of a group, system must wait this interval before sending the first bit of a flag. It is measured from the falling edge of the start pulse of the last bit transmitted by SQ713x.

Note 4: Bus Timeout: SQ713x devices will wait for a Wake Token if the bus is inactive longer than this duration.

Page: 17/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet

3.7 EEPROM Characteristics


Parameter	Min.	Тур.	Max.	Unit
Write Endurance (Sector Endurance)	100,000	-	-	Cycles
Data Retention(at 25°C)	100	-	-	Years
Data Retention(at 85°C)	20	-	-	Years


Ċ


Page: 18/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.


Appendix A. Package Information

SOP8










-					
Symbol	mm				
Symbol	Min.	Тур.	Max.		
А	-	-	1.75		
A1	0.10	-	0.25		
A2	1.25	-	-		
b	0.31	-	0.51		
с	0.10	-	0.25		
D	4.90 BSC				
Е	6.00 BSC				
E1	3.90 BSC				
е	1.27 BSC				
L	0.40	-	1.27		
h	0.25	-	0.50		
θ	0° – 8°				

Page: 19/23 iMQ reserves the right to change the information in this document without prior notice. Please contact iMQ to obtain the latest version of product specification before placing your order. Use of iMQ devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all damages, claims, suits or expenses resulting from such use.



Appendix B. Ordering Information

When ordering products, please provide the following details:

Ordering Information	Product	Packing	Provisioning Service	Description
	SQ7131SP008C00R	Т	Y	I2C, SOP8, Tape & Reel, 85°C, provisioning service
	SQ7131N3008C00R	т	Ν	I2C, DFN 3x3, Tape & Reel, 85°C, no provisioning service
Example	SQ7133SP008S00R	т	Y	SPI, SOP8, Tape & Reel, 85°C, provisioning service
Lxample	SQ7133N3008S00R	т	Ν	SPI, DFN 3x3, Tape & Reel, 85°C, no provisioning service
SQ7135SP008W00R		т	Y	SWI, SOP8, Tape & Reel, 85°C, provisioning service
	SQ7135N3008W00R	Т	Ν	SWI, DFN 3x3, Tape & Reel, 85°C, no provisioning service

Note 1: "Packing"- T: Tape & Reel; B: Tube/Tray

Note 2: "Provisioning service for Customers" - Y: Need provisioning service for customers; N: No need for provisioning service from customers

Page: 21/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.

iMQ Technology Inc.	
No. : TDDS01-S7131-EN(B) Name : SQ7131/SQ7133/SQ7135 Brief Datasheet	Version : V1.6
Appendix C. Product Number Information	
Example : SQ 71 31 SP 008 C 00 iMQ SQ product	<u>R T Y</u>
Product Series	
Sub Series	
Package Type	
Code Package Type SP SOP	
N3 DFN 3x3	
Pin Count	
Code Pin	
008 8	
Communication Interface	
Code Type.	
C I2C	
S SPI W SWI	
Designator	
Operating Temp	
CodeOperating Temp.R-40~85°C	
K	
Packing	
T T&R	
B Tube	
Provisioning Service	
Code Provisioning Y Yes	
N No	
Page : 22/23	
Page: 22/23 iMQ reserves the right to change the information in this document without prior notice. Please the latest version of product specification before placing your order. Use of iMQ devices in life so buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and al or expenses resulting from such use.	contact iMQ to obtain upport is entirely at the
buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMQ from any and all or expenses resulting from such use.	l damages, claims, suits

Revision History

C

Version	Approved Date	Description	
V1.6	2025/4/23	1.Sync with the full datasheet V1.6	
V1.5	2024/4/18	1. Add SQ7135 SWI (Single Wire Interface) info	
V1.4	2024/2/5	1. Add 3.6.3 SPI Characteristics SPITiming Sequence"tSPI"	
V 1.4	V1.4 2024/3/5	2. Add Appendix B. Product Number Information	
		1. Sync with datasheet V1.3 full version	
		2. Add PRODUCT number : SQ7131SP008C00R, SQ7131N3008C00R,	
V1.3	V1.3 2023/12/14	V1.3 2023/12/14 SQ7133SP008S00R, SQ7133N3008S00R	
		3. Modify Supply Current in Operation MODE(During ECC Command	
		Execution) in Appendix B to 7mA	
V1.0	2023/1/18	1. 1 st version issue	

Page: 23/23 iMO reserves the right to change the information in this document without prior notice. Please contact iMO to obtain the latest version of product specification before placing your order. Use of iMO devices in life support is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless iMO from any and all damages, claims, suits or expenses resulting from such use.